



SUB METERED ONE CIRCUIT ELECTRIC HEAT, STORED WATER AND AC/ASHP

INSTRUCTIONS:

- Stearns Electric Association will not be responsible or liable for any personal injury or property damage in the wiring of or the operation of this or any Energy Wise system. Stearns Electric Association recommends the use of a licensed electrical contractor.
- All wiring must meet N.E.C. (National Electrical Code) and be inspected by a state electrical inspector before Stearns Electric Association will check out installation.
- Any time power is off & restored to the radio receiver, there will be a 15-minute time delay before unit will be allowed to operate.
- Radio receiver/meter socket should be mounted 4' to 6' above the ground outside of all structures with ample access around unit.
- Opposite phases of electrical circuits must go through C.T. in opposite directions, CHECK PHASING.
- C.T. must be shunted until meter is installed by Stearns Electric.
- The (A) phase of electric heat power is wired to the terminal strip in the meter socket.
- The (B) phase of water heater power is wired to the terminal strip in the meter socket.
- The "Y" circuit of the AC/ASHP is wired to the terminal strip in the meter socket.

